



## **CHARGING INSTRUCTIONS**

## **RELION R4000 DRY SERIES BATTERIES**

To maximize the life of your R4000 Dry Series batteries use the following charge parameters. A lead-acid flooded battery charger can be used, if the settings are within the parameters of R4000 batteries.

R4000 batteries can be charged with either a 3-step constant current, constant voltage, constant voltage (CC-CV-CV) profile or a 3-step constant current, constant voltage, constant current (CC-CV-CC) profile.

## **CC-CV-CV Charge Profile - 3 Step**

2-STEP CHARGE DESCRIPTION	STEPS	DESCRIPTION	CHARGE PARAMETERS				
Step 1 - Charge at a constant current until the battery reaches absorption voltage.	1	Recommended Charge Current	0.1C20 - 0.2C20				
		Maximum Charge Current	0.25C20				
		SYSTEM VOLTAGE	12V	24V	36V	48V	
Step 2 - Hold absorption voltage until charge reduces to transition current.	2	Absorption Voltage	14.4V – 14.7V	28.8V - 29.4V	43.2V - 44.1V	57.6V - 58.8V	
Step 3 – Hold float voltage until battery is needed or 8 hours, whichever occurs first.		Transition Current	≤0.02C20				
	3	Float Voltage	13.8V	27.6V	41.4V	55.2V	
	Stop	Maximum Float Time	8 hours				

## CC-CV-CC Charge Profile - 3 Step

2-STEP CHARGE DESCRIPTION	STEPS	DESCRIPTION	CHARGE PARAMETERS				
Step 1 - Charge at a constant current until the battery reaches absorption voltage.	1	Recommended Charge Current	0.1C20 - 0.2C20				
		Maximum Charge Current	0.25C20				
Step 2 - Hold absorption voltage until charge reduces to finish current.	SYSTEM VOLTAGE		12V	24V	36V	48V	
	2	Absorption Voltage	14.4V - 14.7V	28.8V - 29.4V	43.2V - 44.1V	57.6V - 58.8V	
Step 3 – Hold finish current until termination criteria is met.	3	Finish Current	≤0.02C20				
	Stop	Termination Criteria	dv/dt = 2.5mV/cell/hr. or 110-115% recharge				

To maximize the life of your battery, the charger should have temperature compensation. For temperatures above 77°F (25°C) subtract: 3mV/cell/1°F (5mV/cell/1°C) and for temperatures below 77°F (25°C) add: 3mV/cell/1°F (5mV/cell/1°C).

For more information please contact Relion technical support.

2017 Relion Battery, Lt.C. All rights reserved, Relion Battery is not liable for damages that may result from any information provided in or omitted from this publication, under any circumstances. Relion Battery reserves the right to make adjustments to this publication at any time, without notice or obligation.

