

**Inverter
Remote Control**
Pure Sine Wave

Model
SSW-R1-12B



Design Features

- Mountable remote control panel for use with SSW Series 1000, 1500 and 2000 Watt inverters
- Informative LCD display indicates:
 - Battery voltage
 - Output power (bar graph)
 - Input fault
 - Output fault
- Use the control panel for remote operation and convenient status monitoring.
- Comes with 10' cable.
- Remote is included with every SSW Series 1000, 1500 and 2000 Watt Model!
- Also sold separately for installations where multiple remote control panel locations are required

2 YEAR WARRANTY

MODEL NO.	SSW-R1-12B
APPLICABLE MODELS OF INVERTERS	SSW-1000-12A SSW-1500-12A SSW-2000-12A
RECEPTACLE FOR CONNECTING CABLE	8P8C (8 Position, 8 Conductor) Modular Receptacle (RJ-45)
CONNECTING CABLE TYPE	8 Conductor, Cat 5 Networking Cable
CONNECTING CABLE, LENGTH	3 meters / 10'
CONNECTING CABLE, CONNECTORS	8P8C (8 Position, 8 Conductor) Modular Plugs (RJ-45) on both ends, straight
DIMENSIONS (WITHOUT CABLE),MM (L x W x H)	102 x 82 x 35
DIMENSIONS (WITHOUT CABLE), IN (L x W x H)	4.0 x 3.2 x 1.4
WEIGHT (WITHOUT CABLE), KG	0.056
WEIGHT (WITHOUT CABLE), LB	0.12