SPOWERSYNC

POWERSYNCLithiumIronPhosphate(LiFePO4)batteries are designed as a drop-in replacement of leadacid batteries.Each of our batteries are designed asreplacements for specific deep cycle lead acid batteriesup to BCI Group Size 8D.Use the table below to crossreference our LiFePO4acid batteries.

These batteries offer a significant longer cycle life and longer float/calendar life than lead acid batteries while helping to minimize replacement cost and reduce total cost of ownership. LiFePO4 batteries are designed for 10,000 Cycles at 50% DOD, 6,000 Cycles at 80% DOD, and 2,000 Cycles at 100% DOD.

In general LiFePO4 batteries are capable of attaining approximately 36% more energy per charge. LiFePO4 batteries represent an advancement in safety due to cell design with advanced battery management systems including under and over voltage, over discharge, over current, over temperature, and short circuit protections which ensures safe and efficient operation. Our LiFePO4 batteries are designed to work with quality micrprocessor controlled lead acid chargers.

POWERSYNC has achieved a point of maximum energy, safety, and market viability. As the cost of bringing LiFePO4 products to market continues to improve, for the first time it makes sense to replace lead acid batteries with LiFePO4 technology.

Lead Time: All in stock items ship next business day. Payment Terms: Net 30 for pre qualified companies. Shipping: FOB POWERSYNC Energy Solutions warehouse.

Warranty: 3 Year Limited Warranty

	Voltage	Voltage Capacity		Charge Discharge		narge	Dimensions						
Model	(V)	(Ah)	Reserve Min @25 A	Max Cont. (A)	Max Cont. (A)	Max Pulse (A)	Energy (Wh)	Length (in.)	Width (in.)	Height (in.)	Weight (Ibs.)	Terminal	Drop In Replacement for the Following Battery Type
LFP6.4-4.5	6.4	4.5	10.8	4.5 = 1C	4.5 = 1C	8 = 2C	29	2.76	1.85	4.00	4.20	T1	PS-645 / UB645
LFP12.8-4.5	12.8	4.5	10.8	4.5 = 1C	4.5 = 1C	8 = 2C	58	3.50	2.75	4.00	1.50	T1	PS-1250 / UB1250
LFP12.8-7.5	12.8	7.5	18	7.5 = 1C	15 = 2C	20 = 2.6C	96	5.85	2.50	3.70	2.40	T2	PS-1270 / UB1270
LFP12.8-12	12.8	12	29	12 = 1C	24 = 2C	30 = 2.5C	154	6.00	3.88	3.74	3.75	T2	PS-12120 / UB12120
LFP12.8-18	12.8	18	43	18 = 1C	36 - 2C	50 = 2.7C	230	7.13	3.00	6.63	6.00	Т3	PS-12180 / UB180
LFP12.8-26	12.8	26	62	30 = 1.1C	30 = 1.1C	40 = 1.5C	333	6.50	6.88	5.00	9.30	M5	PS-12260 / UB12260
LFP12.8-33	12.8	33	79	33 = 1C	50 = 1.5C	60 = 1.8C	422	7.63	5.00	6.25	10.60	T5	Group U1 / PS-12350 / UB12350
LFP12.8-40	12.8	40	96	40 = 1C	70 = 1.75C	80 = 2C	512	7.63	6.50	6.75	14.30	M6	PS-12400
LFP12.8-50	12.8	50	120	50 = 1C	70 = 1.4C	80 = 1.6C	640	10.00	5.25	7.88	18.00	M6	UB-12500
LFP12.8-75	12.8	75	180	70 = 0.9C	70 = 0.9C	100 = 1.3C	960	10.00	6.50	8.38	23.80	M6	Group 24 / PS-12750 / UB12750
LFP12.8-100	12.8	100	240	100 = 1C	100 = 1C	120 = 1.2C	1,280	12.88	6.75	8.38	30.00	M8	Group 31 / PS-121100 / UB12100
LFP12.8-200	12.8	200	480	120 = 0.6C	120 = 0.6C	140 = 0.7C	2,560	18.50	9.13	8.63	65.30	M8	Group 8D / PS-122500 / UB-8D
LFP12.8-250	12.8	250	600	120 = 0.5C	120 = 0.5C	140 = 0.6C	3,200	18.50	9.13	8.63	65.30	M8	Group 8D / PS-122500 / UB-8D
LFP12.8-500	12.8	500	1200	250A = 0.5C	250A = 0.5C	300A = 0.6C	6,400	24.00	24.00	10.00	156.00	M8	Steel Case / Stackable
LFP25.6-50	25.6	50	120	50 = 1C	50 = 1C	75 = 1.5C	1,280	12.88	6.75	8.38	30.00	M8	Group 31 / PS-121100 / UB12100
LFP25.6-100	25.6	100	240	120 = 1.2C	120 = 1.2C	140 = 1.4C	2,560	18.50	9.13	8.63	65.30	M8	Group 8D / PS-122500 / UB-8D





Contact us for more information about our Energy Storage Systems (ESS) including high capacity scalable cabinet battery systems and a comprehensive line of lead acid solutions including Flooded, AGM, GEL, and OPzV chemistries.

SPOWERSYNC In Several Solutions

POWERSYNC Energy Solutions Info@powersyncenergy.com www.powersyncenergy.com (877) 459-4591 Due to continuing product improvements, POWERSYNC reserves the right to change specifications without notice. For most current data, please contact your POWERSYNC Energy Solutions representative. Rev 1-8H28 © 2018 POWERSYNC Energy Solutions, LLC

LiFePO4 (Lithium Iron Phosphate) Drop in Replacements for Lead Acid Batteries