


PMX MS SERIES INVERTER

THE POWERMAX PMX SERIES OF POWER INVERTERS ARE DESIGNED TO PROVIDE CLEAN 120 VOLT AC POWER FOR MANY APPLICATION FROM A 12VDC BATTERY OR BANK. OUR POWERMAX MODIFIED SINE WAVE INVERTERS OUTPUT IS CAPABLE OF EFFICIENTLY RUNNING A WIDE VARIETY OF ELECTRONIC DEVICES SUCH AS OFFICE EQUIPMENT, COMPUTERS, AND HOME ELECTRONICS, TV, STEREO'S, AND MORE.

200 WATT



400 WATT



800 WATT



STANDARD FEATURES:

- DIGITALLY CONTROLLED MODIFIED SINE WAVE OUTPUT
- 12V DC TO 115V AC MEETS 120V ELECTRONIC OPERATING SAFETY STANDARDS
- 2 110V AND 1 USB OUTLETS
- LED STATUS INDICATOR LIGHTS
- INTERNALLY MOUNTED COOLING FAN
- LOW VOLTAGE ALARM
- 1 YEAR WARRANTY

MODEL NUMBER	PMX-200MS	PMX-400MS	PMX-800MS
CONTINUOUS POWER/ SURGE	200/400W	400/800W	800/1600W
DC INPUT VOLTAGE	≤0.8Amp	≤800mA	≤800mA
AC OUTPUT VOLTAGE	115±10%V. RMS	115±10% RMS	115±10% RMS
AC OUTLETS/USB	2 / 1	2 / 1	2 / 1
TYPICAL EFFICIENCY	>80%	≥85%	≥85%
OUTPUT WAVE FORM	Modified Sine	Modified Sine	Modified Sine
SHORT CIRCUIT, OVERLOAD GROUNDING PROTECTION	Yes	Yes	Yes
DIMENSIONS	5.4 x 3.9 x 2.2in	6.3 x 4 x 2.6in	7.5 x 4.7 x 3in
WEIGHT WITHOUT/WITH CABLE	0.93 / 1.19 lbs	1.41 / 1.75 lbs	2.54 / 2.87 lbs



BATTERY CHARGERS / MAINTAINERS
INVERTERS
POWER SUPPLIES
AC-DC CONVERTERS
AUTOMATIC TRANSFER SWITCHES

20 YEARS EXPERIENCE.
POWERMAX PM3 ARE INDUSTRY STANDARD.
SUPPLYING OVER 20 DIFFERENT INDUSTRIES
(941) 201-8041
POWERMAXCONVERTERS.COM