

POWERMAX



PM3 SERIES

CONVERTER / CHARGER - 110V AC TO 12V DC

FEATURES INCLUDE:

- 3 STAGE SMART CHARGING
- FIXED POWER SUPPLY MODE
- VARIABLE VOLTAGE ADJUSTMENT
13VDC TO 16.5VDC
- WORKS WITH ANY BATTERY TYPE
- LED STATUS INDICATOR LIGHT
- INTERNALLY MOUNTED COOLING FAN
- 3 YEAR WARRANTY



MODEL NUMBER	PM3-35LK	PM3-45LK	PM3-55LK	PM3-60LK	PM3-65LK	PM3-75LK	PM3-100LK
DC OUTPUT VOLTAGE (NO LOAD) APPROX.	14.6/13.6/13.2V						
MAX AMP OUTPUT CONTINUOUS	35 amps	45 amps	55 amps	60 amps	65 amps	75 amps	100 amps
MAX POWER OUTPUT CONTINUOUS	510 watts	650 watts	800 watts	875 watts	910 watts	1095 watts	1460 watts
MAX AC CURRENT	8 Amps	9 Amps	11 Amps	11 Amps	11 Amps	13 Amps	15 Amps
TYPICAL EFFICIENCY	>85%	>85%	>85%	>85%	>85%	>85%	>93%
FAN CONTROL	Proportional						
REVERSE POLARITY, OVERLOAD AND THERMAL PROTECTION	Yes						
DIMENSIONS	7.8 x 9.5 x 3.5						
WEIGHT	7.0 lbs	8.0 lbs	9.0 lbs				

BATTERY CHARGERS | MAINTAINERS | INVERTERS | GENERATORS
 DC POWER SUPPLIES | CONVERTERS | POWER CENTERS
 AUTOMATIC TRANSFER SWITCHES

(941) 201-8041
 POWERMAXCONVERTERS.COM