

PMX SERIES INVERTER

THE POWERMAX PMX SERIES OF POWER INVERTERS ARE A DESIGNED TO PROVIDE CLEAN 120 VOLT AC POWER FOR MANY APPLICATION FROM A 12VDC BATTERY OR BANK. OUR POWERMAX PURE SINE WAVE INVERTER OUTPUT IS CAPABLE OF EFFICIENTLY RUNNING A WIDE VARIETY OF DEVICES SUCH AS POWER TOOLS, OFFICE EQUIPMENT-COMPUTER, KITCHEN APPLIANCES-MICROWAVES AND HOME ELECTRONICS-TV, STEREO'S, AND MORE.

STANDARD FEATURES:

- DIGITALY CONTROLLED PURE SINE WAVE OUTPUT
- 12V DC TO 115V AC MEETS 120V ELECTRONIC OPERATING SAFETY STANDARDS
- GFCI AND USB OUTLETS
- LED STATUS INDICATOR LIGHTS
- INTERNALLY MOUNTED COOLING FAN
- REMOTE FUNCTION (AVAILABLE)
- 1 YEAR WARRANTY



MODEL NUMBER	PMX-1000W	PMX-2000W	PMX-3000W
CONTINUOUS POWER/ SURGE	1000W/2000W	2000W/4000W	3000W/6000W
DC INPUT VOLTAGE	11 - 15Vdc	11 - 15Vdc	11 - 15Vdc
AC OUTPUT VOLTAGE	115±10% RMS	115±10% RMS	115±10% RMS
AC OUTLETS/GFCI/USB	2 / 1 / 1	2 / 1 / 1	4 / 2 / 1
TYPICAL EFFICIENCY	>80%	>80%	>80%
OUTPUT WAVE FORM	Pure Sine Wave	Pure Sine Wave	Pure Sine Wave
SHORT CIRCUIT, OVERLOAD THERMAL PROTECTION	Yes	Yes	Yes
DIMENSIONS	10.5 x 8.2 x 3.5	13.1 x 8.8 x 3.8	14.8 x 10.3 x 4.5
WEIGHT	6.1 lbs	9.2 lbs	12.8 lbs

BATTERY CHARGERS / MAINTAINERS
INVERTERS
POWER SUPPLIES
AC-DC CONVERTERS
AUTOMATIC TRANSFER SWITCHES

20 YEARS EXPERIENCE.
POWERMAX PM3 ARE INDUSTRY STANDARD.
SUPPLYING OVER 20 DIFFERENT INDUSTRIES
(941) 201-8041
POWERMAXCONVERTERS.COM